

### 3015B Dual Output Power Supply

- 0 to  $\pm 30V$  with  $\pm 1.5A$  load current
- Energy saver design allows cooler operation
- Excellent Load, line and Ripples specs
- Front panel indicators for Constant Current and Constant Voltage operation
- Each output has two 3 digit LED displays for monitoring Voltage and current



**3015B**

### 3032B Dual Output Power Supply

- 0 to  $\pm 30V$  with  $\pm 3.0$  Amps load current
- Low noise Linear supply for powering sensitive circuits
- Fully isolated outputs for connecting outputs in series
- Excellent Load, line and Ripple specs
- Energy Saver design for cooler operation



**3032B**

## ■ SPECIFICATIONS

### [ 3015B ]

Outputs 1 and 2

Volts: 0 to  $\pm 30V$  DC

Amps: 0 to  $\pm 1.5A$

Constant Voltage Mode:

Load Regulation: 0.02% + 2mV

Line Regulation: 0.02% + 2mV

Ripple and Noise: 1mV RMS

Constant Current Mode:

Load Regulation: 0.05% + 5mA

Line Regulation: 0.05% + 0.25mA

Ripple and Noise: 2mA RMS

Digital Display:

Resolution: Volts: 100mV; Current: 10mA

Accuracy:  $\pm(0.5\% + 3d)$

General Specifications

AC Input Voltage: 120/220V

Power Consumption: 150VA, 50/60Hz

Operating Temperature: 0 to 35°C (32 to 95°F)

Size: 6.3" (H)  $\times$  9.2" (W)  $\times$  12.8" (D)

Weight: 16.5 lbs

Supplied Accessories: Manual, Line cord, Test Leads (2 sets)

### [ 3032B ]

Outputs 1 and 2

Volts: 0 to  $\pm 30V$  DC

Amps: 0 to  $\pm 3A$

Constant Voltage Mode:

Load Regulation: 0.02% + 2mV

Line Regulation: 0.02% + 2mV

Ripple and Noise: 1mV RMS

Constant Current Mode:

Load Regulation: 0.05% + 5mA

Line Regulation: 0.05% + 0.25mA

Ripple and Noise: 2mA RMS

Digital Display:

Resolution: Volts: 100mV; Current: 10mA

Accuracy:  $\pm(0.5\% + 3d)$

General Specifications

AC Input Voltage: 120/220V

Power Consumption: 300VA, 50/60Hz

Operating Temperature: 0 to 35°C (32 to 95°F)

Size: 6.3" (H)  $\times$  9.2" (W)  $\times$  12.8" (D)

Weight: 20 lbs

Supplied Accessories: Manual, Line cord, Test Leads (2 sets)